

# Installation and Setup

After you have installed 3CXphone for Android, you must configure it to use a Ecallnepal voip service in order to make calls. After you have obtained an account at a Ecallnepa details of a VoIP PBX, you must proceed to configure a connection to that account in 3CXphone dialer as follows:

1. Start 3CXPhone by touching the 3CXPhone phone icon. The first time you start 3CXPhone, it will automatically prompt you to create a new connection profile. Click the "Add New" button to create a new profile.
2. Enter a name for the new profile in the field "Profile name"
3. You will get the following field:
  - a. NAME: 1122334455 ( can be any,preferred name is your phone number)
  - b. DISPLAY NAME: 1122334455 ( can be any,preferred name is your phone number)
  - c. USER: This will be provided by Ecallnepal after you sign up
  - d. ID: (id and username is same)This will be provided by Ecallnepal after you sign up
  - e. Password: \*\*\*\*\* This will be provided by Ecallnepal after you sign up.
  - f. SERVER SETTING: Tap **Internal server** and fill with "sip.ecallnepal.com"
  - g. SERVER PORT: 5060

**Leave other section as it is.**

Click Save to create the connection profile. This new profile will be displayed in the "Profiles" page. Once you have logged in successfully, your user name will be shown at the top on the right hand side



Click Save, press the green button next to the profile you wish to use and the 3CXPhone for Android will register.

If you need any help with any other questions, please contact us at:

email/msn : support@ecallnepal.com

tel: 1-323-331-9123

OR you can chat with us @ ONLINE SUPPORT at our website homepage [www.ecallnepal.com](http://www.ecallnepal.com)

Ecallnepal support

[www.ecallnepal.com](http://www.ecallnepal.com)